



Product Code	OSA-ACY-70045
Description	<p>Rainjoy Lumos shower 1000X750mm RGB LED front panel with AISI 304 stainless steel base plate included remote control & installation kit for false ceiling</p> <ul style="list-style-type: none"> - Chromo therapy (RGB): LED 94.5W with 12V 5A Power Supply (SMPS) Including Controller, connecting to AC 100-240V, 50-60Hz - 3-functions <ul style="list-style-type: none"> - Rain - Waterfall - 6 X Mist
Flow Rate	<p>Rain - 48.00 LPM @ 3 bar Waterfall - 44.30 LPM @ 3 bar Mist - 3.55 LPM @ 3 bar</p>
Recommended Water Pressure	2.0 - 4.0 Bar Min.
Min & Max Water Temperature	5°C ~ 75°C
Mount Type	Ceiling Mounting
Spray Modes	Rain, Waterfall & Mist Functions
Material Composition Specification in Percentage	<p>STAINLESS STEEL: Nickel 8.0-11.0, Chromium 18.0-20.0, Manganese 0.0 - 2.0, Carbon 0.0-0.08, Iron Remainder (AISI 304)</p> <p>Acrylic: Acrylic 6T = 6mm thick Acrylic sheet.</p>
REMOTE CONTROL	<p>RGB Remote Control Remote Option : RGB Working Voltage: 3Vd c Wireless Frequency: 2.4GHz Working Temperature: -5C-55C</p>
IP Rating	<p>1- LED Panel (IP4) 2- SMPS Box (IP7) which includes RGB controller inside</p>

LED Specification	RGB LED Voltage : 12Vdc (minimum electricity goes through LED panel for the user safety) RGB LED Watt : 94.5W
POWER SUPPLY	Power Supply (SMPS) Including Controller INPUT : AC 100-240V, 50-60Hz OUTPUT : 12V - 5A
RGB Color Variations	<p>• COLOR VARIATION •</p> <div style="display: flex; justify-content: space-around; align-items: center;"> <div style="text-align: center;"> <p>Mono Color (RGB)</p>  </div> <div style="text-align: center;"> <p>Chromo Therapy</p>  <p>LED On / Off Switch Sensor by Remote Control</p> </div> </div>

DISCLAIMER: Our every effort has been made to ensure factual accuracy, the information presented subject to changes due to requirements in different sites, markets and/ or countries. 10% variation in flow rate may be possible. Jaquar reserves the right to make the necessary amendments at any time without prior notice.